

זוג אוזניות איכותיות Pizzi EarBuds תצוגה דיגיטלית בעברית מלאה



דגם PZ-5230

- מאפייני המוצר**
- גרסת Bluetooth: 5.4
 - תאימות למסייע קולי: Siri
 - בקרת מגע: נגינת / השהיית נגינת מוסיקה, רצועת שירים הבאה / האחרונה.
 - הגברת / הנמכת עוצמת קול, קבל / סיים / דחה שיחה, מסייע קולי.
 - מצב ANC
 - שקע טעינה: Type-C
 - תומך בטכנולוגיית ENC+ANC
 - עם מסך מידע LCD / הפעלה/כיבוי Hall
 - תומך ב- 21 שפות

מפרטים טכניים

גרסת Bluetooth	5.4
תמיכה	A2DP, AVRCP, HSP, HFP
תדר Bluetooth	20 הרץ - 20 קילו הרץ
טווח Bluetooth	10 מטרים
סוללת אוזניות	40 mAH
סוללת בסיס טעינה	400 mAH
זמן טעינה	1.5 שעות

-1-

תכולת המארז
המוצר מכיל את התכולה הבאה. במידה ואחד הפרטים שלהלן חסרים, אנא צרו איתנו קשר באופן מיידי.

מספר (סידורי)	פריטים	כמות
1	אוזניות אלחוטיות Ture	1
2	כבל טעינה Type-C	1
3	מדריך למשתמש	1

לפני השימוש בפעם הראשונה
מצב אחסון הספק מיוחד:
אנא הטעינו את המארז בעזרת כבל הטעינה. לחץ/י לחיצה ארוכה 3 שני על לחצן האיפוס הנמצא ליד שקע הטעינה לקבלת מסך hello, החלק ימינה/שמאלה למסך בחירת שפה ובחר עיברית

-2-

הפעלה חוזרת: פתחו את המארז הטעינה, האוזניות יפעלו באופן אוטומטי.
כיבוי: הכניסו את שתי האוזניות למארז הטעינה, וסגרו את המארז הטעינה. שתי האוזניות ייכבו באופן אוטומטי.

חיבור אוזניות למכשיר הטלפון שלכם:
1. פתחו את המארז הטעינה, האוזניות יעברו שיוך TWS באופן אוטומטי.
2. הפעילו את פונקציית Bluetooth על המכשיר שלכם, לאחר מכן חפשו את PZ-5230 והקליקו עליו לחיבור.
טיפ: אוזניות ייכבו באופן אוטומטי במקרה של היעדר חיבור למכשיר כלשהו תוך 5 דקות.

הוראות למסך המגע של קופסת הטעינה
מסך זה תוכל לשלוט על הפונקציות הבאות:

- *נגינה / השהיית נגינה *שמע מרחבי
- *השיר הקודם / השיר הבא *טוונן בהירות מסך(אור)
- *הגברת עוצמת הקול *שינוי שפה
- *הנמכת עוצמת הקול *רקע למסך (נייר הארנק)
- *מצב ANC(השתקת סביבה) *אוזניות ימין/שמאל
- *הגדרת אקוויזר(משווה) *בקר מצלמה
- *טיימר (זמן) *פתיחת תאורה

-3-

תפעול מגע מהאוזניות עצמן:
מעבר לשיר הקודם
הקליקו שלוש פעמים על MFB על אוזנייה שמאל/ימין.

מעבר לשיר הבא
הקליקו שלוש פעמים על MFB על אוזנייה שמאל/ימין.

דחיית שיחה
לחצו לחיצה ארוכה על MFB במשך 2 שניות על אוזנייה שמאל/ימין.

שימוש במסייע קולי / Siri
לחצו לחיצה ארוכה על MFB במשך 2 שניות על אוזנייה ימין.

מצב ANC
לחצו על לחצן MFB במשך 2 שניות על אוזנייה שמאל למעבר למצב רגיל - הפעלת ANC - מצב שקיפות

הגברה / הנמכה של עוצמת קול
הקליקו פעם אחת על MFB באוזנייה ימין להגברת עוצמת הקול.
הקליקו פעם אחת על MFB באוזנייה שמאל להנמכת עוצמת הקול.

-4-

הוראות בטיחות

1. יש לאחסן אוזניות במקום יבש ומאוורר על מנת למנוע מגע עם שמן, אדים, לחות, אבק וכו', במטרה למנוע פגיעה באיכות הביצועים של המוצר.
2. הימנעו משימוש בחומרי ממס אורגניים שגורמים לגירוי או בפריטים המכילים מרכיבים אלה לניקוי האוזניות.
3. יש לעשות שימוש באוזניות בצורה נכונה ובדרך תקינה בהתאם לנדרש, ויש לשים גם לב להשפעת השימוש על הסביבה. על מנת להבטיח חיבור חלק, המרחק בין מכשיר הטלפון לבין האוזניות צריך להיות בטווח של 10 מטרים.
4. במידה ולאוזניות יש בעיות אחרות כגון חיבור לא טוב או תקשורת לא טובה, נא לא לפרק את גוף האוזניות ואת האביזרים ללא אישור, אחרת האחריות לא תהיה בתוקף.
5. אנא בחרו במטען סטנדרטי למכונת או במטען מתאים שהוקצב על ידי החברה שלנו להטענת האוזניות.
6. על מנת לוודא שימוש רגיל באוזניות, אנא וודאו שהאוזניות טעונות מספיק.

-5-

Pizzi TRUE WIRELESS EARBUDS



Model PZ-5230

- PRODUCT FEATURES**
- Bluetooth version: 5.4
 - Voice assistant compatible: siri
 - Touch control: music play/pause, next/last track,
 - Volume +/-, accept/end/reject call, voice assistant,
 - ANC Mode
 - Charging port: Type-C
 - Support ANC+ENC technology
 - With touch LCD screen / Hall switch on/off
 - Support 21 languages

TECHNICAL SPECIFICATIONS

Bluetooth version	5.4
Support	A2DP,AVRCP,HSP,HFP
Bluetooth Frequency	20HZ-20KHZ
Bluetooth range	10m
Earbuds battery	40mAH
Charging case battery	400mAH
Charging time	1.5h

-1-

PACKAGE CONTENTS

The product contains the following contents. If any of the following items are missing, please contact us immediately.

S/N	Items	Qty
1	Ture Wireless Earbuds Unit	1
2	Type-C Charging Cable	1
3	User Manual	1
4	L Size Eartip	2
5	S Size Eartip	2

BEFORE FIRST USE
Special power storage mode: please charge the case with the charging cable, the screen will light up to exit the storage mode.



-2-

Power ON: Open the charging case, earbuds will power on automatically.

Power OFF: Put both earbuds into the charging case, and close the charging case, both earbuds will power off automatically.

CONNECTING EARBUDS TO YOUR PHONE

1. Open the charging case, earbuds will TWS pair automatically.
2. Turn on Bluetooth on your device, then you can search "F11" and click it to connect.

Tips: Earbuds will automatically power off if don't connect with any device within 5mins.

TOUCH SCREEN SERVICE

- | | |
|---------------------------|-------------------|
| Play/Pause | Spatial Audio |
| Previous Song / Next Song | Adjust Brightness |
| Volume + | Language Switch |
| Volume - | Wallpaper |
| ANC Mode | Find Earbuds |
| Equalizer Setting | Camera Control |
| Stop Timer | Open Light |

Note: Control functions may vary as per the device connected.

-3-

Going to Previous Song
Triple click MFB on L earbud

Going to Next Song
Triple click MFB on R earbud

Refuse Call
Long press MFB for 2 seconds on L/R earbud

Using Voice Assistance /Siri
Long press MFB for 2 seconds on R earbud

ANC Mode
Long press MFB for 2 seconds on L earbud to change Normal Mode- ANC On -Transparency Mode

Volume+/-
Single click MFB on R earbud to increase volume
Single click MFB on L earbud to decrease volume

Note: Control functions may vary as per the device connected.

-4-

SAFETY INSTRUCTIONS

1. Earbuds should be stored in a dry and ventilated environment to avoid contact with oil, steam, moisture, dust, etc., to avoid affecting product performance.
2. Avoid using irritating organic solvents or items containing these ingredients to clean earbuds.
3. Earbuds should be used correctly and in a standardized manner as required, and attention to the impact of the use environment as well. To ensure smooth connection, the distance between the phone and earbuds should be within 10 meters.
4. If earbuds has other problems such as poor connection or communication, please do not disassemble the earbuds body and accessories without permission, otherwise the warranty will not be granted.
5. Please choose a standard car charger or a qualified charger designated by our company to charge the earbuds.
6. To ensure your normal use of earbuds, please ensure that the earbuds has sufficient power.

-5-